QMS® magicolor® WX User's Guide—Addendum

Clearing Service Messages

After your manual was printed, a new configuration menu option called Service Mode was developed to allow you to clear any warning message that doesn't automatically clear after you've taken the necessary corrective action.

For example, you'll need to use this option when you replace a developer cartridge to remove the REPLACE *x* DEVELOPER message.

The following table indicates how to use this new option.

Press this key	to...	The message window reads...
Online/ Offline	Turn off the Online indicator, so you can access the configuration menu.	IDLE
Menu	Access the Display Language menu.*	DISPLAY LANGUAGE ENGLISH
Menu	Advance to the Set Energy Save menu.	SET ENERGY SAVE TIME OUT = 1 HR
Menu	Advance to the Service Mode menu.	SERVICE MODE

Press this key	to...	The message window reads...
Select	Select Service Mode to clear the warning message and save all configuration selections (including the Tray Select key selection).	SERVICE MODE
Online/ Offline	Exit from the menu and ready the printer to accept new print jobs.	IDLE

*The first menu and option that display will be the last ones that were previously accessed.

1800446-001A

QMS, *magicolor*, and the QMS logo are registered trademarks of QMS, Inc.

Copyrighted © 1996 by QMS, Inc., One Magnum Pass, Mobile, AL 36618.